

MAAG-G312 MAAG-G314

4K@60Hz 18G HDMI 2/4 Port USB 3.0 KVM Switch
with Audio & Hotkey Control

► Specifications

		MAAG-G312	MAAG-G314
Console Port		1	
Computer Port		2	4
Front Panel Push Button		1	4
EDID Copy Button		1 (Rear)	
Automatic Scan Interval		3, 8, 15, 30 Seconds	
Cable Length (Max)		3M (10ft) for USB	
EDID LED Indicator		1	
Computer ON-LINE LED		2	4
Computer Selected LED		2	4
Power LED Indicator		1	
Hot Plug-and-Play		Yes	
Console Interface	USB 3.0	USB-A x 1 (Rear) USB-A x 1 (Front)	
	USB HID	USB-A x 3 (Rear) USB-A x 1 (Front)	
	Monitor	HDMI	
	3.5mm Audio Jack	Speaker x 1	
Computer Interface	USB 3.0	USB-B x 2	USB-B x 4
	Monitor	HDMI x 2	HDMI x 4
	3.5mm Audio Jack	Speaker x 2	Speaker x 4
Hotkey		Yes	
Resolution		3840x2160@60Hz (4:4:4)	
DDC2B		Yes	
H x W x D (mm)		40 x 220 x 100	44 x 220 x 130
Power Supply		DC 12V	

► Features

- 2/4 Computers Share Different USB Peripherals
- Supports Video Resolution Up to **4K@60Hz**
- **4K@60Hz HDR 10 Support**
- **HDCP 2.2 Compliance** (DDC Pass Through)
- **Auto EDID & EDID Copy** Function Ensure Uninterrupted Video Playback
- 2 Ways Control Methods for Easy Selection : **Front Panel Push Buttons**
Hotkey Control
- Buzzer Sound for Switching Confirmation
- **Auto & Manual Scan** Function , Scan Time Selectable
- Keyboard & Mouse **Plug-n-Play**, No Software & Drivers Required
- Support Windows & MAC
- Support Audio (Speaker), Also Support HDMI Audio
- **USB Ports at Both Front & Rear Pannels** Provide Connectivity to Both Long Term & Temporary USB Devices
- **USB 3.0 Ports Provide Excellent I/O Speed**



MAAG-G314

UHD 4K@60Hz 4:4:4

HDR 10

HDCP 2.2

► Connection Pattern

